



BsafeTM/400e Secure Gateway

VERSION 2.7.X FOR TCP/IP & SNA

Uninstall Instructions Summary

We suggest that you print this document so it may assist you during the uninstall procedure.

This summary is intended to assist you to quickly uninstall **Bsafe/400e**. It consists of instructions and commands required for complete and successful uninstall of the product on AS/400 and of the GUI on PC.

Uninstall Instructions:

1. Inactivate the Bsafe/400e: in the 5250 product manager go to System -> Bsafe/400e Activation and select "N" for all the servers.

2. In the command line type

```
WRKREGINF
```

and delete the following:

```
QIBM_QSY_CHG_PROFILE
```

```
QIBM_QSY_CRT_PROFILE
```

```
QIBM_QSY_DLT_PROFILE
```

3. Restart TCP/IP.

4. Remove the following libraries:

```
RMTFIL
```

```
RMTOBJ
```

```
RMTSMP
```

5. In the command line execute:

```
ENDTCPSVR SERVER (*HTTP) HTTPSVR (BSAFEINST) .
```

Good Luck!